

REMOTE ZONE PAGING MIC & CHIME ZONES

LTS.PM62

This new digital matrix range allows to realise multizone and multisources installation. This range offers number control possibilities and extensions.



The PM62 remote paging console works together with P68M mixer for remote control and announcement. Its 6 zones selectors provide a direct control interface for use to easily control and zone paging. The alarm button will automatically activate the pre-recorded message 3 over other aux inputs. It could be power supplied by the mixer within 50m, while extra DC 24V power supply is needed when distance is more. The 2 RJ45 communication ports is used to communicate with the mixer and next paging console. Dip switch could be distinguished by the mixer makes 6 paging sonless work simultaneously possible.



LTS.P68M

APPLICATIONS

- General sound,
- Meeting room,
- Public place,
- Sport center,
 - Shops,
- National education,
 - Malls, ...

Specifications

Sensitivity	±5 mV / 600Ω
S/N ratio	> 68 dB
Frequency response	100 Hz ~ 17 KHz (+1, -3 dB)
Phantom power	+ 12V
Bass	±12 dB @ 100 Hz
Trebles	±12 dB @ 10 KHz
Chime	2 tones active for contact free in priority and BGM
Distortion	> 0.1%
Power supply	DC 24V
Dimensions	230 x 150 x 56 mm
Weight	1 kg