

6-ZONE DIGITAL PREAMPLIFIER

LTS.P68M



The P68M provides 3 LINE inputs, a priority MIC line input with phantom power supply, a gain control, a chime with level control and a digital player recorder (for three 60 seconds messages)

This 6-zone mixer integrates all functions to record a message : Microphone, input and output level settings. These messages can be broadcasted once or continuously (thanks to a selector on the rear panel) A connector for priority control is on the rear panel.

This new range of preamplifiers is a perfect public address solution for small and medium sized areas. With the P68M, you will be able to set up quality installations.

Specifications

Sensitivity	$\pm 5 \text{ mV} / 600\Omega, \pm 500 \text{ mV} / 10\text{k} \Omega$
S/N ratio	>68 dB
Frequency response	50 Hz ~ 17 kHz (+1, -3 dB)
Phantom power	+48V
Tuner and tape input sensitivity / impedance	200 mV / 47 Ω
CD input sensitivity / impedance	500 mV / 47 Ω
Auxiliary inputs S/N ratio	>90 dB
Auxiliary inputs frequency response	20 Hz ~ 20 KHz (+1, -3 dB)
Control	Bass : $\pm 12 \text{ dB}$ at 100 Hz / treble : $\pm 12 \text{ dB}$ at 10 kHz
Distortion	>0.05%
Power supply	~230V / 50 Hz & DC 24V
Dimensions	484 x 332 x 88 mm (19" x 2U)
Weight	5.60 kg