

350W AMPLI - PREAMPLI

LTS.PAT5350

This new pre-amplifier range embedded 3 integrated source players, 1 MP3 CD player, 1 SD player and 1 digital tuner.



For amplifier part, this product has :
4 outputs : 350W, 70V – 100V and 4 - 16 Ohms, 1 5 zones switchable selector on the front face, 1 tone corrector 2 bands bass – treble and 1 volume controller on the front face. The general level indicator is seen by a LED bargraph.

For the preamplifier par, this product has :

1 priority MIC input with adjustable Voice Over, 1 line AUX input by RCA, 1 line Pre Out output by RCA.

This model also embedded a MP3 CD player, 1 digital tuner AM/FM with automatic research, 50 memories and a SD player. A direct access to the tracks and functions can be do on the front panel pad. A weekly timer in also integrated to facilitate the tracks and messages diffusion setting. To finish, the PAT5350 is protected from short-circuit, overheating and overload. This model is provided with its infrared remote.

Specifications

Power supply	350W
Output	70 – 100V & 04 – 16 Ohms
MIC inputs	Jack
Sensitivity / impedance	5mV / 600 Ohms
AUX 1 & AUX 2 inputs	RCA
Sensitivity / impedance	350mV / 10K Ohms
Line pre out unbalanced outputs	XLR
Sensitivity / impedance	1V / 600 Ohms
Frequency response	80 Hz – 16kHz (+/- 1.5 dB)
S/N ratio	> 105 dB
THD distortion	<1 %
Tone bass 100 Khz & treble 10 kHz	+/- 10 dB
AM / FM tuner	FM 87 – 108 MgHz AM 522-1611 MgHz
Cooling	By slaved mechanical ventilation
Supply	AC 230V / 50 Hz
Power consumption	450 W
Dimensions	483 x 88 x 446 mm (19" x 3 U)
Weight	21.80 kg