

CONFERENCE - INFRARED MAIN STATION LC3.IRTX



Thanks to the use of 2-band 8MHz frequency, lighting systems can not disrupt the operation of the system. The sensitivity of each audio input can be adjusted separately. The infrared heater must be connected to the main station via a BNC cable.

Many modes are available : work, conference, emergency or free.

Specifications

Channel	8 CHs
Modulation mode	Digital wireless base station
Frequency range	2 - 8MHz
Audio processor	IR-DSP
Frequency response	30 ~ 20000Hz
Distorsion	< 0.2%
S/N ratio	> 90dB
Power supply	AC 110 / 220V
Input level	2V p-p
Impedance output	75Ω
Audio conference input	RCA X8
Emergency audio input	RCA X2
Free audio input	RCA X2
Digital output	BNC X6
LCD display	2.8" display
Dimensions	483×350x89mm
Weight	8kg
Installation	19" rack cabinet
Associated products	LC3.IRR25 / LC3.IRRC08 / LC3.IRH