## 

## DIGITAL DIMMER 6X6KW





This portable dimmer 100% digital on 16 bits is 4U 19" and controlled in DMX512 1990. It is design for many applications and control every charge type. The flight case mounting brackets are included.

## **Specifications** Dimmer equipped with a gradable output • Single CEE 32A sockets (P17) LED Automatic compensation of the supply Equipped with a 30mA differential switch voltage 63A Tetra Choice of the dimmer response time : Presence Data indication 20ms, Holding function outputs in case of no • 80ms or 160ms Data Single-phase or three-phase power Single dimmers control between 0 and supply 100% DMX512 input / output on XLR5 • DMX address single or in group Programming keyboard with LCD display Optional flight case with handles on the front panel Auto-regulated silent fans 20 memories controlled with manual or automatic mode Each dimmer output can be limited between 110 and 245V Four preinstalled curves + custom curves: Linear, S-curve, Extraction, Square and Protected by a DPN 32A circuit breaker User-Defined Curves

