

STEREO PREAMPLIFIER 6 INPUTS LTS.P62



The P62 provides 6 inputs of which 2 balanced MIC inputs with phantom power supply. It also has a stereo and a REC output. On the front panel, each MIC input has bass, treble and level controls.

On the rear panel, the level of each line input can be adjusted : MIC inputs can be set with a selector. A terminal block is on the rear panel to connect an external security system.

Specifications

Inputs	MIC 1 - 2 : Balanced 4 mV - 45 mV / 600Ω MIC 1 - 2 (LINE) : Balanced 150 mV - 1.5V / 10k Ω LINE 1, 2, 3, 4 : Unbalanced 250 mV - 2.5V / 10k Ω
XLR output	1V / 600Ω Impedance : 775 mV / 600Ω
Frequency response	20 Hz - 20 kHz (±1 dB)
Tone	Bass : ±10 dB @ 100 Hz / treble : ±10 dB @ 10 kHz
Phantom power	+ 48V
Power supply	AC 230V / 50 Hz
Power consumption	100W
Dimensions	484 x 209 x 44 mm (19" x 1U)
Weight	3.9 kg

Rear panel diagram

