

HF IP65 WIRELESS DMX INTERFACE LLD.WDMXIP



This DMX LLD.WDMXIP is a wireless interface which can be used in outdoor to control many lighting equipments. It is simple use and easy to install.



Applications

- Architectural
- Outdoor use
- Live show ...

Specifications

Box	DMX HF IP65, each box can be transmitter or receiver
Frequency	2.45GHz, free selection frequency between 2400MHz - 2524 MHz
Control distance	250m
Receiver	16 receivers for 1 transmitter max.
Channels	512 DMX channels by receiver
Transmitter	Possibility to use many transmitters at the same place, on different frequencies 8192 DMX channels by transmitter max.
Power supply	100 - 240V
Dimensions	210x150x70mm
Weight	0.50Kg