

AM / FM TUNER

LTS.AFT

This professional range of audio sources is intended for audio systems installations «public address» quality.



This professional tuner has a memory of 100 AM & FM stations. Easy to use, the AFT offers an automatic or manual search function. The FM frequency band is from 87 to 108MHz and the AM is from 522 to 1611kHz. On the front panel, a wide LCD display and four buttons are here to control the internal program. On the rear panel, there is a RCA audio stereo analog output and connectors for the antenna. This product is delivered with a remote control and AM-FM antennas.

APPLICATIONS

- General sound
- Public place
- Sport Center
- Commerce
- Shopping center
- Restaurant, ...

Specifications

Stations research mode	Synthesizer PLL quartz
Frequency response	FM : 87 - 108 MHz AM : 522 - 1611 kHz
Sensitivity	FM : 20 uV AM : 6.0 mV / m
S/N ratio	FM : > 40 dB AM : > 36 dB
Power supply	AC 230V / 50 Hz
Power consumption	8W
Dimensions	484 x 350 x 88 mm (19" x 2U)
Weight	4.40 kg